

1WT_SMnt_RJ45 Comm Details

To get sensor values:

44 (convert temp)
B800 (copy 1st page to scratch pad)
BE00FFFFFFFF (read page 0 from scratchpad)
018813 D6 00 (example response)

byte0 01 status byte

byte1 88 lsb of temp
byte2 13 msb of temp

byte3 D6 lsb of supply voltage
byte4 00 msb of supply voltage

Temp = hex 1388 = decimal 5000 : $5000 / 256 = 19.53125$ DegC